

## DC 0-100V 10A Voltmeter and Ammeter Panel Meter

Small size, portable, the magnitudes of voltage and current are displayed in the same screen simultaneously.



### **Specifications:**

- Supply voltage: 4.5 - 30V (wide range)
- Voltage measurement range: DC 0-100V
- Current measurement range: DC 0-10A
- Display screen: 0.28 inch LED
- Operating current: <20mA
- Measuring speed:  $\geq 500\text{ms}$  / times
- Accuracy: 1% ( $\pm 1$  word)
- Minimum operating voltage: +4.5 V
- Maximum operating voltage: +30 V
- Operating Humidity: 10~80%
- Operating temperature: -10~+65
- Operating pressure: 80 ~ 106kPa
- 10A inbuilt Shunt

**Wiring:**

- Red line thin: power supply+
- Black line thin: power supply -
- Red line (thick): PW+, measuring terminal voltage input positive
- Yellow line (thick): IN+, current input
- Black line thick: COM, common measuring